

Power Meter Instruction


Description

The Power Meter measures energy power only. You can discover which appliances are the worst energy consumers and then limit their consumption.



Operation:

Plug the power meter into the AC-socket, then plug the electric appliance you want to measure into the socket of the Meter.



Mode Button operation:

Press the MODE-button, LCD display switches between Watts of energy used to Voltage. Power → Voltage → Power

Long press “MODE” button to start with the setting of Electrical unit cost /kWh.



Dotted-Button:

By pressing the Dotted-button, LCD screen displays information total energy consumption, cumulative Electrical cost, energy consumption & electrical cost of customized period, electrical unit cost.

How to set electrical unit cost?



Press Dotted-button to display “electrical unit cost” as below, then long press MODE button till the figures start flickering. Press Dotted-button to increase or MODE button to decrease the values, finally confirm the setting by long pressing the MODE button.

Warning

- For indoor use only
- Position the meter that the meter can easily be disconnected from the mains
- Only free of electrical current when disconnected from mains

Technical data

Operation voltage:	220/230/240V
Frequency:	50/60Hz
Operation current:	Max. 16A / 3680W
Voltage working range:	200V - 276V
Voltage accuracy:	+/- 2%
Power display range:	0.1 W - 3680W
Power accuracy:	+/- 2%
Total kWh display:	0.000 kWh - 9999 kWh